



**ROUGH SERVICE LAMPS** are designed for heavy duty use such as building site application where a more robust lamp is required. They are built to withstand shocks, bumps and vibration.

A19



A21



A23



Order code	Description		Watts (W)	Base	Volts (V)	Finish/Colour	Average life (hrs)	Filament	Lumens (lm)	Case qty
<b>A19</b>										
MOL : 4 1/4 in. (108 mm) LCL : 3 1/2 in. (77 mm)										
61799	50A19/F/RS/130V/STD/2P	(2 pack)	50	E26	130	Frost	5 000	C-7A	360	120
61800	60A19/F/RS/130V/STD/2P	(2 pack)	60	E26	130	Frost	5 000	C-7A	520	120
61801	75A19/F/RS/130V/STD/2P	(2 pack)	75	E26	130	Frost	5 000	C-7A	680	120
61802	100A19/F/RS/130V/STD/2P	(2 pack)	100	E26	130	Frost	5 000	C-7A	1 050	120
<b>A21</b>										
MOL : 5 3/16 in. (135 mm) LCL : 3 7/16 in. (90 mm)										
52134	100A21/F/RS/130V/STD		100	E26	130	Frost	5 000	C-7A	1 050	60
50073	150A21/F/RS/130V/STD		150	E26	130	Frost	5 000	C-7A	1 750	60
<b>A23</b>										
MOL : 6 3/16 in. (157 mm) LCL : 5 1/2 in. (128 mm)										
50087	150A23/F/RS/130V/STD		150	E26	130	Frost	5 000	C-7A	1 750	60
50074	200A23/F/RS/130V/STD		200	E26	130	Frost	5 000	C-7A	2 500	60

# Rough Service Lamps